AMENDMENTS TO THE CLAIMS

This listing of claims will replace all prior versions, and listing, of claims in the application:

Listing of claims:

1. (CURRENTLY AMENDED) A method of forming a semiconductor device comprising:
   a) forming a gate structure over a substrate being doped with a first conductivity type impurity;
   b) performing a doped depletion region implantation by implanting ions being ~~the~~ a second conductive type ~~to~~ into the substrate to form doped depletion regions; ~~beneath and separated from said source/drain regions;~~
   c) performing a S/D implantation ~~implant~~ by implanting ions having a the second conductivity type into the substrate to form ~~S/D~~ source and drain regions adjacent to said gate structure; the doped depletion regions are beneath and separated from said source and drain regions;
      (1) said doped depletion regions ~~have~~ having an impurity concentration and thickness so that said doped depletion regions are depleted due to a built-in potential created between said doped depletion regions and said substrate.

2. (CURRENTLY AMENDED) The method of claim 1 wherein said doped depletion ~~region~~ regions are not formed under said gate structure.

3. (CURRENTLY AMENDED) The method of claim 1 which further includes said doped depletion regions ~~have a~~ having an impurity concentration so that ~~the~~ a built-in

junction potential between said doped depletion regions and said substrate forms depletion regions in the substrate between the ~~source/drain~~ source and drain regions and the doped depletion regions ~~region~~;

said depletion regions have a net impurity concentration of the first conductivity type.

4. (CURRENTLY AMENDED) The method of claim 1 which further includes said doped depletion regions ~~have a~~ having an impurity concentration so that ~~the~~ a built-in junction potential between said doped depletion regions and said substrate forms depletion regions in the substrate between the ~~source/drain~~ source and drain regions and the doped depletion region; said depletion regions have a net impurity concentration of the first conductivity type;

said depletion regions have a net impurity concentration between 1E16 to 5E18 atom/cc.

5. (CURRENTLY AMENDED) The method of claim 1 which further includes implanting ions of ~~a~~ the first impurity type into said substrate between said ~~source/drain~~ source and drain regions and said doped depletion regions.

6. (CURRENTLY AMENDED) The method of claim 1 which further includes performing an implant type selected from the group consisting of Halo implant, threshold voltage implant, and a field implant, that implant ions of ~~a~~ the first impurity type into said substrate at least between said ~~source/drain~~ source and drain regions and said doped depletion regions.

7. (CURRENTLY AMENDED) The method of claim 1 wherein ~~the~~ a region of said substrate between said source/drain regions and said doped depletion regions has a concentration of ~~a~~ the first conductivity type impurity between 1E16 to 1E18 atom/cc; a channel region in said substrate under said gate structure; said channel region has a concentration of a second type impurity between 1E16 to 1E18 atom/cc.

8. (CURRENTLY AMENDED) The method of claim 1 wherein said doped depletion regions are fully depleted.

9. (CURRENTLY AMENDED) The method of claim 1 which further includes performing LDD implantation by implanting ions being a the second conductivity type into the substrate using the gate structure as a mask to form LDD regions.

10. (CURRENTLY AMENDED) The method of claim 1 which further includes performing a LDD implantation by implanting ions being a the second conductivity type into the substrate using the gate structure as a mask to form LDD regions;

the LDD regions are formed before the doped depletion regions.

11. (CURRENTLY AMENDED) The method of claim 1 which further includes performing a LDD implantation by implanting ions being a the second conductivity type into the substrate using the gate structure as a mask to form LDD regions;

wherein the doped depletion regions are formed after the LDD regions.

12. (CURRENTLY AMENDED) The method of claim 1 wherein said first ~~conductive~~ conductivity type is p-type and said substrate has a boron concentration between 1E17 to 1E19 atom/cc.

13. (CURRENTLY AMENDED) The method of claim 1 wherein said first ~~conductive~~ conductivity type is n-type and said substrate ~~100~~ has a an As or P concentration between 1E 17 to 1E 19 atom/cc.

14. (CURRENTLY AMENDED) The method of claim 1 wherein said ~~first conductive~~ type substrate is comprised of Si or SiGe or strained Si, or relaxed SiGe or strained Ge.

15. (ORIGINAL) The method of claim 1 wherein said gate structure has a channel width between 0.04 and 0.5 μm.

16. (ORIGINAL) The method of claim 1 which further includes performing a LDD implantation by implanting ions being a the second conductivity type into the substrate using the gate structure as a mask to form LDD regions;

the LDD implantation is performed by implanting As ions at a dose between 5E14 and 1E16 atoms /cm^2, at an energy between 1 keV and 10 keV.

17. (ORIGINAL) The method of claim 1 which further includes performing a LDD implantation by implanting ions being a the second conductivity type into the substrate using the gate structure as a mask to form LDD regions;

the LDD implantation is performed by implanting Boron ions at a dose between 1E14 and 5E15 atoms /cm^2, at an energy between 1 keV and 10 keV.

18. (CURRENTLY AMENDED) The method of claim 1 wherein the doped depletion region implantation is performed by implanting As or P ions at a ~~does~~ dose between 5E12 and 5E13 atoms/cm2, at an energy between 100 keV and 500 keV; said doped depletion region ~~has~~ having a minimum depth below ~~the substrate~~ a surface of said substrate between 0.09 and 0.7 μm.

19. (CURRENTLY AMENDED) The method of claim 1 wherein the doped depletion region implant ~~implantation~~ is performed by implanting boron ions at a ~~does~~ dose between 5E11 and 5E13 atoms/cm2, at an energy between 50 keV and 200 keV; said doped depletion region ~~has~~ having a minimum depth below ~~the substrate~~ a surface of the substrate between 0.09 and 0.7 μm.

20. (CURRENTLY AMENDED) The method of claim 1 wherein the S/D implantation ~~implant~~ is performed by implanting arsenic (As) or phosphorus (P) ions at a dose between 5E14 to 1E16 atoms/cm2, at an energy between 50 keV and 80 keV; said ~~Source/drain~~ source and drain regions ~~have~~ having a depth below ~~the substrate~~ a surface of said substrate of between 0.04 and 0.5 μm.

21. (CURRENTLY AMENDED) The method of claim 1 wherein said second conductivity type is p-type; and said S/D implant is performed by implanting boron ions at a dose between 5E14 to 1E16 atoms/cm^2, at an energy between 50keV and 80keV; said ~~source/drain~~ source and drain regions have a depth below ~~the substrate~~ a surface of said substrate of between 0.04 and 0.5 μm.

22. (ORIGINAL) The method of claim 1 which further includes said gate structure having sidewalls; and forming one or more spacers on the sidewalls of said gate structure.

23. (CURRENTLY AMENDED) A method of forming a semiconductor device comprising:

a) forming a gate structure over ~~on~~ a substrate being doped with a first conductivity type impurity;

b) performing a doped depletion region implantation by implanting ions being ~~the~~ a second ~~conductive~~ conductivity type to the substrate to form doped depletion regions beneath and separated from said source/drain regions;

(1) said doped depletion regions have an impurity concentration and thickness so that said doped depletion regions are depleted due to a built-in potential created between said doped depletion regions and said substrate;

~~(2) said doped depletion regions have a impurity concentration so that the built in junction potential between said doped depletion regions and said substrate forms depletion regions in the substrate between the source/drain regions and the doped depletion region; said depletion regions have a net impurity concentration of the first conductivity type; said depletion regions have a net impurity concentration between 1E16 to 1E18 atom/cc;~~

c) performing a S/D implantation ~~implant~~ by implanting ions ~~having~~ a being the second conductivity type into the substrate to form ~~S/D~~ source and drain regions adjacent to said gate structure;

(1) said substrate between said ~~source/drain~~ source and drain regions and said doped depletion regions has a concentration of a first type impurity between 1E16 to 1E18 atom/cc[.] ;

said doped depletion regions have an impurity concentration so that the built-in potential between said doped depletion regions and said substrate forms depletion regions in the substrate between the source and drain regions and the doped depletion region; said depletion regions have a net impurity concentration of the

first conductivity type; said depletion regions have a net impurity concentration between 1E16 to 1E18 atom/cc.

24. (CURRENTLY AMENDED) The method of claim 23 wherein said doped depletion regions ~~region~~ are not formed under said gate structure.

25. (CURRENTLY AMENDED) The method of claim 23 wherein ~~the~~ a region of said substrate between said source/drain regions and said doped depletion regions has a concentration of ~~a~~ said first conductivity type impurity between 1E16 to 1E18 atom/cc;
a channel region in said substrate under said gate structure; said channel region has a concentration of a second conductivity type impurity between 1E16 to 1E18 atom/cc.

26.(CURRENTLY AMENDED) The method of claim 23 which further includes; said gate structure has sidewalls; forming one or more spacers on the sidewalls of said gate structure.

27. (CURRENTLY AMENDED) The method of claim 23 which further includes; said gate structure has sidewalls; forming two or more spacers on the sidewalls of said gate structure prior to the doped depletion region implantation.

CLAIMS 28 TO 35 ARE CANCELED

36.(NEW) The method of claim 1 which further includes said gate structure has sidewalls; forming one or more spacers on the sidewalls of said gate structure.

37. (NEW) The method of claim 1 which further includes said gate structure has sidewalls; forming two or more spacers on the sidewalls of said gate structure prior to the doped depletion region implantation.

38. (New) A method of forming a semiconductor device comprising:
forming a gate structure over a substrate being doped with a first conductivity type impurity;

performing a doped depletion region implantation by, using said gate structure as an implant mask and implanting ions being of a second conductive type into the substrate to form doped depletion regions;

performing a S/D implantation by implanting ions of the second conductivity type into the substrate to form source and drain regions adjacent to said gate;

the doped depletion regions are beneath and separated from said source and drain regions; said doped depletion regions have an impurity concentration and thickness so that said doped depletion regions are depleted due to a built-in potential created between said doped depletion regions and said substrate.

39. (New) The method of claim 38 which further includes said doped depletion regions having an impurity concentration so that a built-in junction potential between said doped depletion regions and said substrate forms depletion regions in the substrate between the source and drain regions and the doped depletion regions;

said depletion regions have a net impurity concentration of the first conductivity type.

40. (New) The method of claim 38 wherein said doped depletion regions are fully depleted.